

## 4 x 8 Composite AV Matrix Switch



### FEATURES

- Composite video and stereo audio 4 x 8 Matrix Switch with IR control
- Allows the transmission of 4 x composite baseband video signals and stereo audio signals to up to 8 TV's using 4 pair twisted cable
- Built-in LED's to show acknowledgement of IR commands
- Built-in IR control of Source with addition of RL-IR700/800 Emitter
- Discrete IR capable
- resi-linx® IR control system is plasma/LED panel friendly and Foxtel/iQ compatible
- Includes Switch Mode power supply

RL-BV1000	
For use with	RL-BV150B Receiver /RL-BV500 IR Target
Connections - In/Out	4 x RCA/ 4 x 3.5mm Audio/ 8 x RJ45/ 6 x IR Emitter
Configuration	4:8
IR capability	Yes
Power	12V DC 1.5A Switch Mode
Maximum video input	1.2V P-P
Return loss	>15dB to 1,000 MHz
Common mode rejection	>40dB @ 1,000 MHz
Maximum distance cable	Up to 100m