

3 input / 8 output RF Distribution Module



FEATURES

- Active, low loss combiner and splitter with 3 inputs, 8 outputs
- Includes gain control for Free To Air input to eliminate problems due to high/low signal strength. When combined with gain control on modulator, allows complete balancing of signals
- FM trap On/Off switch to filter 88-108MHz signals from transferring through to output ports to eliminate FM interference to TV reception
- Designed for mounting into Vcomm's Structured Cabling Enclosure

RL-RF380	
Output Frequency Pass	30KHz to 850MHz
Number of output	8
Number of input (Modulator / ANT)	3
Gain / Loss - ANT	+2dB
- Modulator	+3dB
Output run distance	60 metres
Isolation (Modulator inputs to ANT)	-80dB
Weight (g)	405
Size (mm)	135 (l) x 69 (w) x 22 (d)
Power Requirement	12V DC Power Supply
Power Supply	
Power - Input	110 - 240V AC
- Output	12V DC - 1.5A Switch Mode
Connections - Power Out	1.8mm length with F-2.1mm mini jack